



FUTURE
SYSTEMS

HFOz/Radtel Network

HFOz/Radtel User's Guide

Document Producer	Checked by	Approved by
Steve Kennedy SENG	Paul McAllan SENG	Steve Kennedy Managing Director

Technical Reference
Steve Kennedy

Date
28/05/2016

Doc #
<doc number>

Rev
A.01

Page
1(24)

Draft

We reserve all rights in this document and in the information contained therein. Reproduction, use or disclosure to third parties without express authority is strictly forbidden.



REVISION HISTORY

Revision	Prepared by	Changes/Comments	Date
A.01	S Kennedy	Reformat	2016-05-28



TABLE OF CONTENTS

1.	Introduction.....	4
1.1	Selcall Number.....	4
1.2	Emergency Assist	4
1.3	Channels and Frequencies	4
1.4	Radtel Billing Procedures.....	5
1.4.1	Option 1	5
1.4.2	Option 2	5
2.	RADIO USER GUIDELINES	6
2.1	Important Information	6
3.	HFOz – GPS and Message Logging	7
3.1	Logging GPS Info and Messages	7
3.2	Accessing GPS Info and Messages.....	7
4.	HF Oz – Email	8
4.1	Email Setup.....	8
4.2	Sending Email from HF Radio	8
4.3	Receiving Emails on HF Radio	9
4.4	Sending Emails from Computer	9
5.	HFOz – SMS to Mobile Phone	10
5.1	SMS Setup 1	10
5.2	Sending SMS to Mobile Phone	10
6.	General.....	11
6.1	RADIO to BASE Operator Emergency Contact (Selcall ONLY)	11
6.2	GENERAL USAGE	11
7.	Summary of Commands.....	11
8.	Terms and Conditions	12
9.	HFOz / Radtel Network Guidelines.....	13
10.	General Information	13
10.1	Emergency Service – ‘Emergency Assist’ plan only.....	13
10.2	Message Service – ‘Emergency Assist’ plan only	13
10.3	Messages Base Operator to Radio.....	13
10.3.1	General Messages.....	13
10.3.2	Emergency Messages	13
10.4	Scan Table for: HFOz and Radtel Network - Land Use and OR Marine use.....	14
11.	Basic Radio Operation.....	15
	APPENDIX A: Phone Contact Lists.....	17
A.1	EAB Phone Contacts List.....	17
A.2	NEB Phone Contacts List	19
A.3	NWB Phone Contacts List	20
A.4	WAB Phone Contacts List.....	21
A.5	CAB Phone Contacts List	22
	APPENDIX B: Network Base Sites	24



1. Introduction

Welcome to HFOz and Radtel HF Radio Network, please find enclosed our info package. We strongly suggest you read all the information supplied and keep it with you for future reference.

The 'HFOz and Radtel info package' contains

- Licence Authority
- Emergency Assist - Operator & Emergency Selcall List (only applicable if option is selected)
- Network Operation Handbook –This is a MUST Read
- Radtel Billing Procedures
- Licence Authority,

This must be signed where it states "Authority Holder" and kept with your radio at all times.

1.1 Selcall Number

Your allocated Selcall Number is XXXX.

1.2 Emergency Assist

Operator & Emergency Selcall List - This is your reference for HFOz and Radtel Channels/Frequencies, Base Operators and Emergency Assist contacts, (e.g., RFDS, Marine Rescue, Police etc), Beacon Numbers and Base Telcall Numbers. All Emergency calls made from this listing are free of charge. N.B. You must be subscribed the Emergency Assist Option to use this facility.

1.3 Channels and Frequencies

Currently HFOz and Radtel has 15 channels and should be entered in the following order;

Table 1 - Frequency List

Channel No.	Freq (kHz)	Channel No.	Freq (kHz)
6	3885 KHz	15	8160 KHz
7	5734 KHz	16	11,016.5 KHz
8	8043 KHz	17	16,240 KHz
9	12,216 KHz	18	11,013.5 KHz
10	15,890.5 KHz	19	16,231 KHz
12	3760 KHz	20	11,450 KHz
13	5105 KHz	21	16,104.5 KHz
14	6910 KHz		



2. RADIO USER GUIDELINES

Due to the structure and features offered by HFOz there is no need to conduct scheduled reporting by our base site operators (skeds). All safety logging is completely controlled by the radio user and hence is the responsibility of the radio user to ensure correct procedures are adhered to. This service once again maximises available airtime for all users.

- Wait at least 20 seconds before sending any transmission
- All voice calls must commence and end by using your call sign, which is the network name followed by your selcall number eg. HFOz 6530
- Tune and listen for "airway traffic" (anyone talking) before transmitting.
- ALWAYS select the best frequency by performing a 'Beacon Call' or 'Channel Test' prior to making the actual call.
- Complete each segment of your conversation with "OVER"
- Try not to dominate channels and consider fellow users.
- If wishing to break in on an existing conversation, simply say "BREAKER" after an over. Then wait to be invited to introduce yourself.
- No inappropriate language or conversation is acceptable.
- We strongly recommend users that have their GPS interfaced with the radio, to daily log their position and also to log 'Messages' to indicate any relevant details pertaining to safety.
- All logged information (GPS Positions and Messages) will be stored in a database for any possible future recall by any relevant safety authority – N.B. This transmitted information is strictly data and NON operator monitored.
- Logged records can also be accessed by your friends, relatives and associates, provided they are given your selcall number and 'User' password.

2.1 Important Information

Please read the following very careful as the points noted below are **EXTREMELY IMPORTANT** for proper operation of HFOz' Email, GPS Logging, Messages and SMS to Mobile Phone

- Wait at least 20 seconds to ensure the channel is free and there is no current transmissions in place
- At the completion of every transmission (HFOz's Email, GPS Logging, Messages and SMS to Mobile Phone, Email Logins) please ENSURE that all data has finished before returning your radio to Scan Mode – It's ABSOLUTELY CRUCIAL to ensure all return revertive messages to our base sites have been sent to complete the various required procedures. Failure to adhere to these procedures may return incorrect or none of the revertives to your radio, that are required for proper operation – It may also interrupt your messages to the radio.

3. HFOz – GPS and Message Logging

HFOz GPS and Message Logging is a service whereby you can log Messages and/or GPS positions to a general web based page for viewing by anyone who has internet access.

This service is a crucial link in providing safe travelling in the outback – Friends Relos, business associates etc can keep tabs on your travels, relevant messages and plot your position indicating your exact location on our topographical mapping server.

3.1 Logging GPS Info and Messages

1. Ensure you have the correct Base Selcall ID for this type of calling e.g., 2010-Newcastle, 6010-Perth, 8010-Central
2. Perform a Beacon or Channel Test as per normal calling procedures before placing the actual call, to acquire the best channel
3. Send GPS Call or Message*^
4. After the call is sent, the base station will send a of series revertive tones to indicate the call was successfully sent and received. N.B. The first revertive tone or message received will only indicate the Base 'Radio' has received the call, which will be followed soon by another revertive 'message' from the HFOz web server. **"YOUR GPS POSITION (or MESSAGE) HAS BEEN LOGGED"** Once and only when this message has been received can you be assured the call has been successfully received and logged by the HFOz Database web server
5. **Please ENSURE you allow at least 60 seconds for this procedure to complete**


3.2 Accessing GPS Info and Messages

Any 'authorised' person who has internet access can access your logging info by the following method.

- Log onto www.hfoz.com.au
- Click on **'Members Login'** tab at top of screen - Selcall Number and 'User' password are required to access logging info
- Enter 'Selcall Number'
- Enter 'User' password as supplied by the radio subscriber (XXXX)
- Logging information will now be displayed

If you wish to display any GPS positions on map, simply tick the appropriate position/s 'check box'

and click on

To **Zoom In**, simply place the mouse near (not on) the desired position and double click the mouse left button, alternatively you can use the  on top left of screen

To **Zoom Out**, Click the  on top left of screen.

To **Move Map**, Hold down mouse left button and drag the map in any direction.

If you wish to select other positions must ensure you close the map screen before selecting another position and then re-load map.



4. HF Oz – Email

4.1 Email Setup

HFoZ Short Text Email facility will allow the radio user to send short text messages, up to 80 characters, (depending on the model of radio and options fitted) to any designated email address. However before any emails can be sent from your radio you must first set-up your pre-programmed email address list.

To set-up HFoZ for email you will need to go to www.hfoz.com.au click on 'Members Login' and log in as 'User' then click on 'My Account' and enter your 'Admin' password, (xxxx) then click on 'Email Set-up' which will allow you to configure your pre-set email addresses (up to a maximum of 99). After entering the 'name' and 'email address' HFoZ will allocate a two digit number to that address. This 2 digit prefix is used when sending emails messages from your radio. The Email Address List can be printed out for easy reference if required. N.B. Email 'Set-up' tab will only show if you are subscribing to the relevant plan.

4.2 Sending Email from HF Radio

1. Ensure you have the correct Base Selcall ID for this type of calling
2. e.g., 2010-Newcastle, 6010-Perth, 8010-Central
3. Perform a Beacon or Channel Test as per normal calling procedures before placing the actual call, to acquire the best channel
4. The email is sent exactly the same way as sending SMS messages but with the inclusion of a # character, 2 digit prefix, and another # character preceding the message e.g., **#02#WE ARE IN THE SIMPSON DESERT AND HAVING GREAT TIME** – Please note that no spaces are required between #02# and the actual text message as shown above.
5. After the call is sent, the base station will send a revertive message 'Call Completed' to indicate the call was received N.B. The first revertive message received will only indicate the Base 'Radio' has received the call, and followed soon by another revertive 'message' from the HFoZ web server "**YOUR EMAIL WAS SENT TO JOHN SMITH**" N.B. The name John Smith is only an example. Once and only when this message has been received can you be assured your email has been successfully sent and logged by the HFoZ Database web server
6. **Please ENSURE you allow at least 60 seconds for this procedure to complete**
7. The above procedures may vary if you have ALE option active



4.3 Receiving Emails on HF Radio

N.B **To receive email messages** you must logon to the network regularly to download any possible emails, as failure to do so may result in your emails being deleted – emails will be stored for a period of 7 days before deletion – Your email 'in box' can only store up to 10 emails – so it's critical to download as frequently as possible.

1. Ensure you have the correct Base Selcall ID for this type of calling
2. e.g., 2010-Newcastle, 6010-Perth, 8010-Central
3. Perform a Beacon or Channel Test as per normal calling procedures before placing the actual call, to acquire the best channel
4. You must now Logon to the base with the channel that you have chosen as the best available – to do this, a string of characters must be sent. Simply send **##** as an SMS/Page Call, that is, double hash
5. The base you are calling will respond with either one of the following messages –
6. **"RECIEVING 2 of 5 EMAILS "** or **"YOU HAVE NO EMAILS"**
7. If you have emails waiting, they will be transmitted one by one as separate messages to your radio – sit back and wait until all the emails have been downloaded to your radio **DO NOT TOUCH ANY CONTROLS ON YOUR RADIO WHILE THIS PROCEDURE IS IN PLACE.**- Various outside sources can sometimes interrupt the transmission which will cease the entire operation – If this occurs you will have to log onto the base site again
8. N.B. You can only download a maximum of 5 emails at anyone time – you will need to logon again if you have in excess of 5 - **Please wait until all messages have been downloaded.**

4.4 Sending Emails from Computer

1. Logon onto www.hfoz.com.au
2. Click on **'Members Login'** tab at top of screen
3. Enter 'Selcall Number'
4. Enter 'User' password as supplied by the radio subscriber
5. Click on **'Send Email'**
6. Enter 'Senders Email Address' and 'Name' where requested
7. Enter the email text in 'Text Box'
8. Click on 'Send Email'
9. Your email will be received when the radio user logs on to the network



5. HFOz – SMS to Mobile Phone

5.1 SMS Setup 1

Sending SMS to mobile phones is on a 'Pre-Paid' call plan structure – Please ensure you have SMS credits, minimum purchase of SMS Credits is 100. Also note that pre-paid plans will cease at the end of your subscription consequently any unused SMS credits will be forfeited at that time.

SMS to Mobile Phone facility will allow the radio user to send short text messages up to a maximum of 80 characters (depending on the model of radio and options fitted) to any designated (pre-programmed) mobile phone number. Before any SMS can be sent from your radio you must first set-up your pre-programmed address list.

Simply go to www.hfoz.com.au click on 'Members Login' and log in as 'User' then click on 'My Account' and enter your 'Admin' password, then click on 'SMS Set-up' which will allow you to configure your pre-set mobile phone numbers (up to a maximum of 99). After entering the 'name' and 'mobile phone number' HFOz will allocate a two digit number to that address. This 2 digit prefix is used when sending SMS messages from your radio as described below. The Address List can also be printed out for easy reference if required.

5.2 Sending SMS to Mobile Phone

1. Ensure you have the correct Base Selcall ID for this type of calling
2. e.g., 2010-Newcastle, 6010-Perth, 8010-Central
3. Perform a Beacon or Channel Test as per normal calling procedures before placing the actual call, to acquire the best channel
4. Sending an SMS to a mobile phone is done in the same way as sending SMS-PageCall messages but with the inclusion of a * character, 2 digit prefix, and a # character preceding the message e.g., ***02#WE ARE IN THE SIMPSON DESERT AND HAVING GREAT TIME** – Please note that no spaces are required between *02# and the actual text message as shown above.
5. After the call is sent, the base station will send a revertive message to indicate the call was successfully sent and received. N.B. The first revertive message received will only indicate the Base 'Radio' has received the call, and followed soon by another revertive 'message' from the HFOz web server. e.g., "**SMS WAS SENT TO TERRY – BALANCE 34**" Once and only when this message has been received can you be assured the SMS was successfully sent.
6. The words '**BALANCE 34**' indicates you currently have 34 SMS credits left
7. **Please ENSURE you allow at least 60 seconds for this procedure to complete**
8. The above procedures may vary if you have ALE option active



6. General

6.1 RADIO to BASE Operator Emergency Contact (Selcall ONLY)

HFOz Base sites are now equipped with up to 5 Operator, Selcall Contact numbers, please note correct operational times for each operator as per Base Site Map. General information can be obtained from this point of contact for any relevant information deemed necessary.

6.2 GENERAL USAGE

HFOz encourages the use of the network for vehicle to vehicle conversation. We especially want to encourage new members or those not familiar with HF to frequently use their radios to become more familiar and confident. Please remember this network is designed to be very family friendly.

* GPS and Message logging SMS to Mobile Phone and Email services are only compatible with Codan NGT, Envoy, 9323 and Barrett 2050.

^ **Message Logging** term means messages that are sent to the general web page – i.e., all Messages will be displayed together on the one page.

7. Summary of Commands

Table 2 - Summary of Commands

Description	Command
General Message and GPS logging	Nil
Sending Email from HF Radio	#01#
Sending SMS to Mobile Phone from HF Radio	*01#
Retrieving Emails from Base sites	##

N.B. The blue numerals above are just an example and this number will vary depending on the number in your email or SMS listing



8. Terms and Conditions

1. By subscribing to HFOz is an agreement to the terms and conditions as listed below.
2. Annual Network Fees (12 months) must be paid in advance
3. HFOz assumes no responsibility for the use and operation of the users radio equipment.
4. HFOz users must abide by regulations as set out by the Australian Communications and Media Authority.
5. HFOz users are not permitted to communicate with non HFOz subscribers sharing the same frequencies
6. HFOz Base Station coverage, is a GUIDE ONLY and may vary from time to time.
7. HFOz will not be responsible for variations in coverage transmission by the Radio Base Stations.
8. GPS Position Logging intervals will be the total responsibility of the radio user.
9. HFOz will provide three (3) base stations for the purpose of GPS Position Logging, Short Message Text transmission, Short Text Emailing, General Message Transmission
10. HFOz accepts no responsibility for GPS Positions, Emails, SMS or SMS-PageCalls that fail to be logged or any fault that may occur within the 'Network', which is out of the control of HFOz.
11. Any unused SMS credits that are remaining at the completion of the 12 month subscription will be forfeited
12. Calls to HFOz Base Site Operators may be recorded for quality assurance.
13. Due to the nature of HF transmissions 'HFOz' will not be responsible for any data corruption that may occur within the network.
14. 'HFOz' reserves the right to vary these Terms and Conditions without notice, as may be deemed necessary.
15. Although we take all reasonable steps to make sure you receive the services within our coverage areas, the service is not free from faults or interruptions. Certain factors, such network congestion, correct operation of radio transceiver, atmospheric conditions, third parties and obstructions or interference may mean you will not receive the service in certain areas at certain times. Where you send, transmit or receive information services as part of the service, we do not warrant the accuracy of the information in, or the security of those services.
16. 'HFOz' reserves the right to suspend, restrict or disconnect any subscriber should the terms and conditions as set out above and also by the Australian Communications and Media Authority not be adhered to.



9. HFOz / Radtel Network Guidelines

This booklet has been produced to enable HFOz and Radtel Network users to obtain the full benefit from the available services. It is imperative that you read and understand the following information fully.

HFOz and RADTEL Operation Hours: 0900 – 1700 WST Monday-Friday *

10. General Information

Radtel Network does NOT provide a service, whereby your friends, business associates etc, can directly dial to your radio. They can only pass messages on via the Radtel base operators using the Message Service as below.

10.1 Emergency Service – ‘Emergency Assist’ plan only

Radtel Network offers a 24 hours¹ emergency assistance. This service is maintained by an operator. Please note this service does not provide medical advice.

10.2 Message Service – ‘Emergency Assist’ plan only

This service is available to friends, relatives and business associates who wish to pass on messages to Radtel users. Anyone who requires to use this facility must adhere to the instructions as noted on this card as shown on page 3.

10.3 Messages Base Operator to Radio

10.3.1 General Messages

These messages will be transmitted ‘On Demand’** during normal business hours. Please note that these messages will only be transmitted ONCE, from which it will then be the responsibility of the radio user to retrieve their messages by calling a Radtel Operator.

10.3.2 Emergency Messages

These messages will be transmitted ‘On Demand’** immediately anytime of day. If first unsuccessful, Radtel Network will continue to transmit these calls at random times until the message has been received or until it is considered all reasonable efforts have been exhausted to transmit the message.

N.B. For message Service to be effective, your radio MUST be scanning the correct channels – See section ‘Channel Scanning’.

10.4 Scan Table for: HFOz and Radtel Network - Land Use and OR Marine use.

Codan 8528/8528S

Barrett 250/550/950 Q-Mac HF90 Codan 9323/9390 Barrett 2050

East / Central	West / Central
Channel 13	Channel 13
Channel 15	Channel 14
Channel 16	Channel 15
Channel 17	Channel 18
Channel 20	Channel 19
Channel 21	Channel 20
Channel 8	Channel 21
Channel 9	Channel 8
Channel 10	Channel 9
	Channel 10

N.B. Marine Users should only require East / West tables

Codan 8525/8528/8528S, Codan 9390 / NGT, Barrett 250/550/980

Australia
Ch 14
Ch 15
Ch 16
Ch 17
Ch 18
Ch 19
Ch 20
Ch 21

Please note that channel numbering may vary according to radio model – Please compare your channel numbering to the actual frequency. Usually Marine radio channel numbers commence in 80xx, e.g., 8012, 8013 etc.

11. Basic Radio Operation

The following instructions are intended for use by radio users who are competent in the operation of their radio –

Radio	Beacon Calling	Selcalling	Radio Telephone
Codan 8528/S	Press 'Selective Call' Enter Beacon No. Press 'Selective Call'	Press 'Selective Call' Enter Selcall No. Press 'Selective Call'	Press 'Selective Call' Enter Base Telcall No. Press 'Enter' Enter Phone No. inc. STD Area Code Press 'Selective Call'
Codan 9323/9390	Press 'Beacon' Enter Beacon No. Press 'Call'	Press 'Call' Enter Selcall No. Press 'Call'	Press 'Call' Enter Base Telcall No. Press 'Enter/Recall' Enter Phone No. <i>inc. STD Area Code</i> Press 'Call'
Barrett 250	Press 'CALL' Enter Beacon No. Press 'SEND'	Press 'CALL' Enter Selcall No. Press 'SEND'	Press 'CALL' Enter Base Telcall No. Press 'CALL' Enter Phone No. <i>inc. STD Area Code</i> Press 'SEND'
Barrett 550/950	Press 'SEL/TEL' Enter Beacon No. Press 'CHAN/SEND'	Press 'SEL/TEL' Enter Selcall No. Press 'CHAN/SEND'	Press 'SEL/TEL' Enter Base Telcall No. Press 'SEL/TEL' Enter Phone No. <i>inc. STD Area Code</i> Press 'CHAN/SEND'
Barrett 2050	Press 'Call' Select 'Beacon' Press 'Enter' Enter Beacon No. Press 'Call'	Press 'Call' Select 'Selcall' Press 'Enter' Enter Selcall No. Press 'Call'	Press 'Call' Select 'Telcall' Press 'Call' Enter Base Telcall No. Press 'Call' Enter Phone No. <i>inc. STD Area Code</i> Press 'Call'

HFOz/Radtel Network
HFOz/Radtel User's Guide

Radio	Beacon Calling	Selcalling	Radio Telephone
Icom F7000	Press 'Call' Select 'Sel Bcon' Enter Beacon No. Press & Hold 'Call'	Press 'Call' Select 'Selcall' Enter Selcall No. Press & Hold 'Call'	Press 'Call' Select 'Telcall' Enter Base Telcall No. Enter Phone No. <i>inc.</i> <i>STD Area Code</i> Press & Hold 'Call'
Q-Mac HF90	Press * Enter Beacon No. Press *	Press * Enter Selcall No. Press *	Press * Enter Base Telcall No. Press # Enter Phone No. <i>inc</i> <i>STD Area Code</i> Press * Press ## to Hang-up Call
Jenal Mic SC2	Enter Beacon No. Press # *	Enter Selcall No. Press # #	Enter Base Telcall No. Press # Enter Phone No. <i>inc</i> <i>STD Area Code</i> Press # Press # 8 to Hang-up
Codan NGT or Envoy	Please refer to your local dealer		

APPENDIX A: Phone Contact Lists

A.1 EAB Phone Contacts List

Name:	Selcall No.	Beacon
Emergency Assist OPERATOR 1 – Bus Hrs WST*	2901	Same
Emergency Assist OPERATOR 2 – After Hours	2902	Same
Emergency Assist OPERATOR 3 – After Hours	2903	Same
Head Office Radtel/HFOz - Bus Hrs WST*	2910	Same
POLICE Albury	2911	Same
POLICE Ballarat	2912	Same
POLICE Bamaga	2913	Same
POLICE Bendigo	2914	Same
POLICE Bourke	2915	Same
POLICE Brisbane	2916	Same
POLICE Broken Hill	2917	Same
POLICE Cairns	2918	Same
POLICE Canberra	2919	Same
POLICE Charleville	2920	Same
POLICE Cloncurry	2921	Same
POLICE Cobar	2922	Same
POLICE Coffs Harbour	2923	Same
POLICE Dubbo	2924	Same
POLICE Griffith	2925	Same
POLICE Hobart	2926	Same
POLICE Lakes Entrance	2927	Same
POLICE Launceston	2928	Same
POLICE Longreach	2929	Same
POLICE Mackay	2930	Same
POLICE Mildura	2931	Same
POLICE Melbourne	2932	Same
POLICE Moree	2933	Same
POLICE Portland	2934	Same
POLICE Port Macquarie	2935	Same
POLICE Rockhampton	2937	Same
POLICE Tibooburra	2938	Same
POLICE Toowoomba	2939	Same
POLICE Townsville	2940	Same
POLICE Tweed Heads	2941	Same
POLICE Wanaaring	2942	Same
POLICE Wilcannia	2943	Same
NRMA	2944	Same
RACQ - QLD	2945	Same
RACT - Tas	2946	Same
RACV - Vic	2947	Same
RFDS Broken Hill	2950	Same
RFDS Cairns	2951	Same
RFDS Charleville	2952	Same



HFOz/Radtel Network
HFOz/Radtel User's Guide

Name:	Selcall No.	Beacon
RFDS Port Augusta	2953	Same
NPWS Armidale	2960	Same
NPWS Broken Hill	2961	Same
NPWS Hunter Region	2962	Same
NPWS Newcastle	2963	Same
NPWS Snowy Region	2964	Same
NPWS Tibooburra	2965	Same
NPWS Bathurst	2966	Same
Rescue Co-ordination Centre (Canberra)	2975	Same
Customs Hotline	2976	Same
Customs National Comm Centre	2977	Same
Ballina – Marine Rescue	2978	Same
Batemans Bay – Marine Rescue	2979	Same
Bermagui - Marine Rescue	2980	Same
Brisbane - Coast Guard	2981	Same
Cape Byron- Marine Rescue	2982	Same
Coffs Harbour – Marine Rescue	2983	Same
Hobart – Coast Radio	2984	Same
Kettering-TAS - Coast Guard	2985	Same
Kingscliff - Coast Guard	2986	Same
Lake Macquarie - Marine Rescue	2987	Same
Melbourne - Coast Guard	2988	Same
Middle Harbour (Sydney) - Marine Rescue	2989	Same
Nelson Bay - Marine Rescue	2990	Same
Newcastle - Marine Rescue	2991	Same
Norah Head - Marine Rescue	2992	Same
O'sullivan's Bch-SA - Coast Guard	2993	Same
Port Augusta SA - Coast Guard	2994	Same
South Aust Sea Rescue	2995	Same
Southport QLD- Coast Guard	2996	Same
Shoal Haven - Marine Rescue	2997	Same
Terrigal - Marine Rescue	2998	Same

Technical Reference
 Steve Kennedy

Date
 28/05/2016

Doc #
 <doc number>

Rev
 A.01

Page
 18(24)

Draft

We reserve all rights in this document and in the information contained therein. Reproduction, use or disclosure to third parties without express authority is strictly forbidden.

A.2 NEB Phone Contacts List

Name:	Selcall No.	Beacon
Emergency Assist OPERATOR 1– Bus Hrs WST*	3901	3999
Emergency Assist OPERATOR 2 – After Hours	3902	3999
Emergency Assist OPERATOR 3 – After Hours	3903	3999
Head Office Radtel/HFoZ - Bus Hrs WST*	3910	3999
POLICE Bamaga	3911	3999
POLICE Brisbane	3912	3999
POLICE Burketown	3913	3999
POLICE Cairns	3914	3999
POLICE Charlieville	3915	3999
POLICE Cloncurry	3916	3999
POLICE Cooktown	3917	3999
POLICE Darwin	3918	3999
POLICE Longreach	3919	3999
POLICE Mackay	3920	3999
POLICE Mount Isa	3921	3999
POLICE Normanton	3922	3999
POLICE Rockhampton	3923	3999
POLICE Townsville	3924	3999
POLICE Weipa	3925	3999
Brisdville Auto	3930	3999
Birdsville Auto A.H.	3931	3999
Mount Dare Homestead	3932	3999
NRMA – NSW	3933	3999
RACQ - QLD	3934	3999
AANT - N.T.	3935	3999
RACT - Tas	3936	3999
RACV - Vic	3937	3999
RFDS Cairns	3950	3999
RFDS Charlieville	3951	3999
RFDS Mount Isa	3952	3999
Customs Hotline	3978	3999
Customs National Comm Centre (48hrs Notice)	3979	3999
Rescue Co-ordination Centre (Canberra)	3980	3999
Brisbane - Coast Guard	3981	3999
Cairns - Coast Guard	3982	3999
Cooktown - Coast Guard	3983	3999
Kettering-TAS - Coast Guard	3984	3999
Southport - Coast Guard	3985	3999
Townsville - Coast Guard	3986	3999
Yeppoon - Coast Guard	3987	3999

A.3 NWB Phone Contacts List

Name:	Selcall No.	Beacon
Emergency Assist OPERATOR 1– Bus Hrs WST*	6901	Same
Emergency Assist OPERATOR 2 – After Hours	6902	Same
Emergency Assist OPERATOR 3 – After Hours	6903	Same
Head Office Radtel/HFoZ - Bus Hrs WST*	6910	Same
POLICE Albany	6911	Same
POLICE Broome	6912	Same
POLICE Carnarvon	6913	Same
POLICE Derby	6914	Same
POLICE Docker River	6915	Same
POLICE Esperance	6916	Same
POLICE Halls Creek	6917	Same
POLICE Kalgoorlie	6918	Same
POLICE Kununurra	6919	Same
POLICE Laverton	6920	Same
POLICE Meekatharra	6921	Same
POLICE Newman	6922	Same
POLICE Perth	6923	Same
POLICE Port Hedland	6924	Same
POLICE Wiluna	6925	Same
RFDS Derby	6929	Same
RFDS Kalgoorlie	6930	Same
RFDS Meekatharra	6931	Same
RFDS Port Hedland	6932	Same
RFDS Port Augusta	6935	Same
NT Aerial Medical Darwin	6936	Same
NT Aerial Medical Gove	6937	Same
NT Aerial Medical Katherine	6938	Same
CALM Broome	6940	Same
CALM Head Office	6941	Same
CALM Derby	6942	Same
CALM Fitzroy Crossing	6943	Same
CALM Kununurra	6944	Same
Capricorn Roadhouse	6945	Same
CANNING Stock Route WELL 33	6946	Same
RAC WA	6947	Same
Birdsville Auto	6948	Same
Bridsville Auto A.H.	6949	Same
Mount Dare Homestead	6950	Same
RAA - S.A.	6951	Same
Customs Hotline	6978	Same
Customs National Comm Centre (48hrs Notice)	6979	Same
Rescue Co-ordination Centre (Canberra)	6980	Same
Albany Sea Rescue	6981	Same
Fremantle Sea Rescue	6982	Same

A.4 WAB Phone Contacts List

Name:	Selcall No.	
Emergency Assist OPERATOR 1– Bus Hrs WST*	7901	7999
Emergency Assist OPERATOR 2 – After Hours	7902	7999
Emergency Assist OPERATOR 3 – After Hours	7903	7999
Head Office Radtel/HFoZ - Bus Hrs WST*	7910	7999
POLICE Broome	7911	7999
POLICE Carnarvon	7912	7999
POLICE Derby	7913	7999
POLICE Esperance	7914	7999
POLICE Ftizroy Crossing	7915	7999
POLICE Halls Creek	7916	7999
POLICE Kununurra	7917	7999
POLICE Meekatharra	7918	7999
POLICE Newman	7919	7999
POLICE Port Hedland	7920	7999
CALM Broome	7940	7999
CALM Derby	7941	7999
CALM Fitzroy Crossing	7942	7999
CALM Kununurra	7943	7999
RAC WA	7947	7999
AANT - N.T.	7948	7999
RFDS Derby	7950	7999
RFDS Meekatharra	7951	7999
RFDS Port hedland	7952	7999
Customs Hotline	7978	7999
Customs National Comm Centre (48hrs Notice)	7979	7999
Rescue Co-ordination Centre (Canberra)	7980	7999
Albany Sea Rescue	7981	7999
Fremantle Sea Rescue	7982	7999

A.5 CAB Phone Contacts List

Name:	Selcall No.	Beacon
Emergency Assist OPERATOR 1– Bus Hrs WST*	8901	Same
Emergency Assist OPERATOR 2– After Hours	8902	Same
Emergency Assist OPERATOR 3– After Hours	8903	Same
Head Office Radtel/HFoZ - Bus Hrs WST*	8910	Same
POLICE Alice Springs	8911	Same
POLICE Yulara (Ayres Rock)	8912	Same
POLICE Adelaide	8913	Same
POLICE Bamaga	8914	Same
POLICE Birdsville	8915	Same
POLICE Broome	8916	Same
POLICE Burketown	8917	Same
POLICE Cairns	8918	Same
POLICE Ceduna	8919	Same
POLICE Cloncurry	8920	Same
POLICE Coober Pedy	8921	Same
POLICE Cooktown	8922	Same
POLICE Darwin	8923	Same
POLICE Derby	8924	Same
POLICE Docker River	8925	Same
POLICE Finke	8926	Same
POLICE Fitzroy Crossing	8927	Same
POLICE Hals Creek	8928	Same
POLICE Kununurra	8929	Same
POLICE Katherine	8930	Same
POLICE Longreach	8931	Same
POLICE Mackay	8932	Same
POLICE Mount Isa	8933	Same
POLICE Normanton	8934	Same
POLICE Port Augusta	8935	Same
POLICE Rock Hampton	8936	Same
POLICE Tennant Creek	8937	Same
POLICE Townsville	8938	Same
POLICE Weipa	8939	Same
POLICE Woomera	8940	Same
CALM Kununurra	8941	Same
CALM Fitzroy Crossing	8942	Same
CALM Broome	8943	Same
Birdsville Auto	8944	Same
Birdsville Auto A.H.	8945	Same
Mount Dare Homestead	8946	Same
RAA - S.A.	8947	Same
AANT - N.T.	8948	Same
RFDS Broken Hill	8952	Same
RFDS Cairns	8953	Same
RFDS Charlieville	8954	Same
RFDS Derby	8955	Same
RFDS Mount Isa	8956	Same
RFDS Port Augusta	8957	Same

 Technical Reference
 Steve Kennedy

 Date
 28/05/2016

 Doc #
 <doc number>

 Rev
 A.01

 Page
 22(24)

Draft

 We reserve all rights in this document and in the information contained therein.
 Reproduction, use or disclosure to third parties without express authority is
 strictly forbidden.



HFOz/Radtel Network
HFOz/Radtel User's Guide

Name:	Selcall No.	Beacon
NT Aerial Medical Darwin	8960	Same
NT Aerial Medical Gove	8961	Same
NT Aerial Medical Katherine	8962	Same
O'Sullivans Bch-SA - Coast Guard	8981	Same
Port Augusta - Coast Guard	8982	Same
South Aust Sea Rescue	8983	Same

Technical Reference
Steve Kennedy
Draft

Date
28/05/2016

Doc #
<doc number>

Rev
A.01

Page
23(24)

We reserve all rights in this document and in the information contained therein. Reproduction, use or disclosure to third parties without express authority is strictly forbidden.

APPENDIX B: Network Base Sites

Network Base Sites - 2015

